



## NEVABOOST 140 230V 12V



### Overview

#### NEVABOOST 140 230V 12V

cod. 807541

Battery charger for charging free electrolyte batteries (WET) with 12 V voltage.

Protected against overloads and polarity reversal.

Equipped with selector for normal, quick charge/help with starting (BOOST&GO) Equipped with ammeter.

### Technical data

<b>CODE</b>	CODE 807541	<b>A<sub>EN</sub></b>	RATED CHARGE CURR. EN60335-2-29 13 A	<b>W<sub>H</sub></b>	DIMENSIONS 17 - 25 - 16,5 cm
<b>V<sub>1PH</sub></b>	SINGLE PHASE MAINS VOLTAGE 230 V	<b>A<sub>1V/C</sub></b>	START CURRENT 1V/C EN60335-2-29 50 / 100 (Boost) A	<b>kg</b>	WEIGHT 5,2 kg
<b>F</b>	MAINS FREQUENCY 50 / 60 Hz	<b>C<sub>MIN</sub></b>	MIN. RATED REFERENCE CAPACITY 10 Ah	<b>BAR CODE</b>	EAN CODE 800489764143 0
<b>P</b>	CHARGING ABSORBED POWER 230 W	<b>C<sub>MAX</sub></b>	MAX RATED REFERENCE CAPACITY 200 Ah	<b>Grid icon</b>	PIECES/PALLET 95 pz/pallet
<b>Battery icon</b>	CHARGING VOLTAGE 12 V	<b>Sun icon</b>	ADJUSTMENT POSITIONS 2	<b>Grid icon</b>	PIECES/PALLET - B 76 pz/pallet - B
<b>A<sub>EFF</sub></b>	EFFECTIVE CHARGING CURRENT 20 A				

### Included Accessories