



## ENERGY 1500 START 230-400



### Overview

#### ENERGY 1500 START 230-400

cod. 829009

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

#### Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



CE MARKING



EAC CERTIFICATION









REMOTE CONTROLS

### Technical data

CODE	CODE 829009	EFFECTIVE CHARGING CURRENT	150 / 250 A	ADJUSTMENT POSITIONS	6
THREE PHASE MAINS VOLTAGE	230 / 400 V	RATED CHARGE CURR. EN60335-2-29	130 / 220 A	DIMENSIONS	38 x 56 x 88,5 cm
MAINS FREQUENCY	50 / 60 Hz	START CURRENT 1V/C EN60335-2-29	1000 / 1300 A	WEIGHT	69 kg
CHARGE POWER	7 KW	MAX STARTING CURRENT	1700 / 2000 A	EAN CODE	800489736540 4



## ENERGY 1500 START 230-400

 START POWER 44 KW	 MIN. RATED REFERENCE CAPACITY 70 A	 PIECES/PALLET 4 pz/pallet
 CHARGING VOLTAGE 12 / 24 V	 MAX RATED REFERENCE CAPACITY 2000 / 4000 A	 PIECES/PALLET - B 6 pz/pallet-B

### Included Accessories

REMOTE CONTROL 6 M - 123993

CABLE 50MMQ 3M-WORK CLAMP - 713260

CABLE 50MMQ 3M-POSITIVE CLAMP-EYELET Ø10 - 713162