



## ENERGY 650 START 230-400V 12-24V



### Overview

#### ENERGY 650 START 230-400V 12-24V

cod. 829385

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



CE MARKING



EAC CERTIFICATION









REMOTE CONTROLS

### Technical data

CODE	CODE 829385	EFFECTIVE CHARGING CURRENT	100 A	ADJUSTMENT POSITIONS	5
THREE PHASE MAINS VOLTAGE	230 / 400 V	RATED CHARGE CURR. EN60335-2-29	80 A	DIMENSIONS	36,5 x 46 x 75,5 cm
MAINS FREQUENCY	50 / 60 Hz	START CURRENT 1V/C EN60335-2-29	640 A	WEIGHT	38 kg
CHARGE POWER	2,5 KW	MAX STARTING CURRENT	1000 A	EAN CODE	800489774452 0



## ENERGY 650 START 230-400V 12-24V

 START POWER 20 KW	 MIN. RATED REFERENCE CAPACITY 20 A	 PIECES/PALLET 9 pz/pallet
 CHARGING VOLTAGE 12 / 24 V	 MAX RATED REFERENCE CAPACITY 1200 / 800 A	 PIECES/PALLET - B 6 pz/pallet-B

### Included Accessories

REMOTE CONTROL 6 M - 123993