

## EO Mini Pro

The smartest fast charging station on the market; designed to charge all available EV's.



### Installation & Warranty

- Simple electrical installation
- Integral 6mA DC leakage detection, no Type B RCD required
- Adjustable maximum charging current for lower rated supplies

### Flexibility

- One of the smallest on the market at 175mm x 125mm x 150mm
- Universal socket
- Power Ratings: Single Phase up to 7.2kW options available
- Design your own, pick a colour and add your logo



Pick a Colour and Add  
Your Logo



## EO Mini Pro Charging Station

MODEL ORDER CODE	EOMINI-PRO
Description	EO Mini Pro 32A 1-Phase Charger
<b>ELECTRICAL DATA</b>	
Rated Power	Up to 7.2kW
Charging Current	6A to 32A (variable)
Rated Current	Up to 32A max.
Nominal Supply	230VAC 50Hz
Supply Connections	L1, N, PE 2.5 - 10mm <sup>2</sup>
Over Current Protection	40A Supply
Earth Leakage Protection	A dedicated 30mA Type A RCD must be used on the supply circuit Integral 6mA DC leakage detection – no Type B RCD required
Standby Power Consumption	<5W
Status Indication	3 colour LED indicator (green, blue, red)
Charging Mode	Mode 3 (IEC 61851-1 / SAE J1772 compliant communication protocol)
Socket	IEC 62196 Type 2, IP54 hinged lid, non-locking
Supply Cable Entry	Ø20mm or Ø25mm hole drilled at site through bottom of enclosure
<b>MECHANICAL DATA</b>	
Dimensions (H x W x D)	175mm x 125mm x 150mm
Unit Weight	1.3Kg
Mounting Location	Wall Mounted, Indoor or Outdoor (permanent mounting).
Ambient Temperature	-10°C to +50°C
Operating Humidity	5 to 95%
Enclosure	ABS (UL94 HB Fire Rated), IK08
Protection	IP54
Standard Finish	Glasiirt 68 Line Paint, Silver (RAL 9006)
<b>COMPLIANCE</b>	
CE Marked, EMC Directive 2014/30/EU, IEC 61851-1, IEC 62196-2 EN55032, 61000-3, 61000-4	
<b>OPTIONS</b>	
Alternative colours, logos and branding available upon request (minimum order quantities apply).	

In no event will EO Charging accept any liability for any loss, costs or damage consequential on the use and/or misuse of our hardware or software products except and only to the extent that this is caused by our negligence.



Warranty terms can be found at [www.eocharging.com/s/EO-Warranty.pdf](http://www.eocharging.com/s/EO-Warranty.pdf)

©2019 EO Charging. All rights reserved. Designed and Manufactured in the United Kingdom.

Issue May-2019